

EM REX - EMERGENCY EXIT DEVICE

Emergency Exit switch for use with Access Control Systems

The Em Rex Emergency Exit Device is an emergency door release unit, which is used on its own or in conjunction with the Prox Rex touch to exit unit to make up a total access control exit setup.

Features:

- This is a field resettable unit
- Used in an access control system to work in conjunction with an exit button to comply with building codes for emergency egress
- No breaking of glass to operate
- Red indication bar also shows when the unit has been activated
- There is also a built-in sounder which operates when activated
- There is also an ancillary input to turn the sounder on remotely
- Matches the Prox Rex unit
- Minimal moving parts
- Text and graphic Lexan overlay is easy to clean and fade resistant



Specification Data:

- 1 gang profile – 75mm x 115mm - fits standard electrical flush box
- Powered requirement 9 to 16Vdc if using on board sounder
- Draws 10ma at 13.6Vdc
- There are 2 sets of NO and NC / voltage-free / dry-contact / outputs
- The contacts are rated at 1amp 12vdc capacitive load
- The faceplate has a Lexan overlay which will not deteriorate over time and easily cleaned.
- CE Certified.



Innovative Electronic Solutions

www.ness.com.au

© 2011 Ness Corporation Pty Ltd ABN 28 069 984 372. Photos are used for illustrative purposes only. Design and specifications may vary.

NSW Ph 02 8825 9222
sales@ness.com.au

VIC Ph 03 9875 6400
nessmelb@ness.com.au

QLD Ph 07 3399 4910
nessbris@ness.com.au

WA Ph 08 9328 2511
nessper@ness.com.au

SA Ph 08 8152 0000
adelaide@ness.com.au